



FEATURES OF THE AMPLICALL 100

- ➔ Loud electronic ringer: **up to 90dB**
- ➔ Adjustable volume
- ➔ 32 different melodies
- ➔ Visual ring indicator
- ➔ 3 alarm settings:
 - Flash + Alarm (+ option to add additional shaker)
 - Flash (+ option to add additional shaker)
 - Alarm (+ option to add additional shaker)
- ➔ Can be paired with up to 6 transmitters, each having their own zone icon on the base
- ➔ Distance between the AMPLICALL 101 ringer and the AMPLICALL100 base: 30 meters. The distance achieved indoors can vary.
- ➔ Flashing light indicators for the battery levels of the main base and the other transmitters
- ➔ Relay output and door opening duration control setting (2 or 5 seconds)
- ➔ AMPLICALL 101 doorbell included

TECHNICAL SPECIFICATIONS OF THE AMPLICALL 100

- ➔ Wall and desk mountable
- ➔ Frequency: 868MHz
- ➔ Operates plugged into the mains supply
- ➔ Can work on batteries in the event of a power failure, the same goes for the vibrating pad available in option (3 x AR14 batteries not included)
- ➔ Dimensions: 14.6 x 17.6 x 5.5cm

FEATURES OF THE AMPLICALL 101 DOORBELL

- ➔ Doorbell for the AMPLICALL 100 and 150
- ➔ Ring light around the button
- ➔ Wall mountable

TECHNICAL SPECIFICATIONS OF THE AMPLICALL 101 DOORBELL

- ➔ Works on 3V CR2032 batteries (included)
- ➔ Low battery alert signal
- ➔ Frequency: 868MHz
- ➔ Dimensions: 3,1 x 7,3 x 2,1 cm

OPTIONAL EXTRAS

- ➔ Vibrating Pad (CLA2)
- ➔ CLA2 EX

COMPATIBLE PRODUCTS

- ➔ AMPLICALL 101 additional doorbell
- ➔ AMPLICALL 110, AMPLICALL 140
- ➔ AMPLICALL150 (only with the Amplicall 101 doorbell included in the pack)